

Display

Channel Number
 Signal Indicator
 Squelch On/Off Indicator
 Volume Level Bars
 Frequency Display

Normal Operations

ON/OFF Press and hold 5 sec.
 Volume Down
 Volume Up
 MODE Press and hold to put unit in "Channel" Change mode. Display will start blinking.

To Change Channels

1 Press and hold until display is blinking.
 2 Press to advance 100 channels at a time.
 3 Press to scroll down.
 3 Press to scroll up.
 4 After locating desired channel, press to "lock" and return to Normal Mode. Display will stop blinking.

Squelch On/Off Control

Squelch is a static filter.
 Squelch "On" indicator. When squelch is on, the squelch indicator light is on.
 1
 2
 3
 4
 The default and recommended setting is "Squelch On". To turn Squelch off — Press 2 and 4 at the same time. To turn Squelch on — Press 3 and 4 at the same time.

How to use your RACEceiver Earphones

1. Compress the foam lengthwise between your thumb and forefinger until you feel the "tube" inside the foam.
2. Then compress the foam around the tube and insert carefully into your ear. Hold for a few seconds, to allow the foam to expand and seal out the outside noise.

Troubleshooting

1. All I hear is static. — Be sure the squelch is on.
2. The display shows numbers counting to 10 over and over. — Change the battery.
3. Does not sound as clear as it did yesterday or this morning. — Change the battery.
4. It sounds a little scratchy or rough. — Back the volume down a notch or two.

Recommendations

1. Don't try "no name" batteries — Use the good ones. A quality AAA battery should last 20–24 hours.
2. Take the battery out after a race.
3. If it rains, try to keep your RACEceiver as dry as possible.

"Hot Jump" Feature

Press Simultaneously to Jump
 After locking on a drivers channel, press both scroll buttons to jump to MRN/PRN. Press again to jump back to your driver's channel.



1600 Elite

A Product of

Innovative Spector Products

742 Main Street, SW, Gainesville, Georgia 30503
866-301-RACE or 866-301-7223

www.raceceiver.com

A word from Innovative Spector Products
Congratulations and thank you for purchasing The RACEceiver 1600 Elite! After years of juggling bulky scanners, we are pleased to be the innovator of the world's first microscanner. We look forward to years of serving your communication needs with a corporate mission built on customer service, value and innovation.

Consumer Warning

Use care in inserting earpieces. Do not force into ears or hearing damage or other injury may occur. Set volume to lowest setting **before inserting earpieces**. Once earpieces are inserted, begin increasing volume to a comfortable level. Inserting earpieces with volume set at a higher level may cause hearing damage.

Driver Warning

When used as one-way communication devices between race control and competitors, Raceceiver should not be relied upon as the sole indication of potential hazards. Caution lights and signals by flaggers and other officials must be observed. The driver should not rely on any warning devices to the exclusion of his own observation of track conditions.

Channel Charts

RACEceiver provides updated channel charts listing the driver's channels online at www.raceceiver.com

Be sure to check out the "printer friendly" channel charts before your favorite racing event!

ACCESSORIES

Visit www.raceceiver.com online for the latest accessories including:

- ★ **Splitters**
- ★ **Headsets**
- ★ **Wrist Straps**
- ★ **Extra Earsets**

WARRANTY

Your RACEceiver 1600 comes with a full 1 year warranty against manufacturer defects, from the date of purchase.

REGISTER YOUR WARRANTY ONLINE!
www.raceceiver.com